

**COMMUNITY BATTERY DESIGN BRIEF
DEDERANG RECREATION RESERVE**

Table of contents

Table of contents	1
1. Site Overview	3
1.1. Solar PV capacity max	3
1.2. Electrical infrastructure and limitations	3
1.3. Preferred output as suggested by modelling.....	3
2. System Design	3
2.1. Recommended System	3
2.1.1. System Summary	3
2.1.2. Site Battery System Details	3
2.2. Design Layout.....	4
2.2.1. Solar PV layout.....	4
2.2.2. Site layout	4
2.2.3. Structural considerations.....	5
3. Delivery	5
3.1. Delivery Plan	5
3.2. Indicative Delivery Costs	5
4. EV Charging Addition.....	6
4.1. Technical Considerations	6
5. Appendix	6
5.1. Site electrical infrastructure	6
5.2. Site structural and layout photos.....	6

1. Site Overview

1.1. Solar PV capacity max

Pylon model suggested the Dederang Memorial Hall could host 16 kW on tilt frames.

1.2. Electrical infrastructure and limitations

The Hall connects to a 10kva transformer. The switchboard is presently capable of 40 amps. Therefore, we expect to be limited to 5kW export capacity at any one time from any solar and battery system. The site would be a DC coupled system due to the fact we will be installing on one building only.

1.3. Preferred output as suggested by modelling

The sites football clubrooms already have 10kW of solar PV and a 13.8kwh battery installed. We would recommend installing 10kw of solar PV and 20kwh of battery storage to the hall.

2. System Design

2.1. Recommended System

2.1.1. System Summary

For sites that have an energy resilience focus a flow battery is recommended.

Solar PV Size	10kW tilt frames
Solar PV Brand	Tier One (Tindo, SunPower, Hyundai, Jinko)
Battery Size	20kWh
Battery Brand	Redflow
Inverter Size	2 x 5kW
Inverter Brand	Deye
Control Device	Mondo UBI
Electrical infrastructure	40-amp Two Phase supply
Grid Connectivity	Connected to a 10kva transformer

2.1.2. Site Battery System Details

Supply and Install 2 x Redflow ZBM3 10kWh battery stacks with Redflow heating system. This system will be coupled with a 5kW Deye Hybrid Inverter and a 5kw on grid inverter. Battery decibel rating is low at no more than 40dB.

2.2. Design Layout

2.2.1. Solar PV layout



2.2.2. Site layout



The dimensions of the proposed battery are:

- Height: 1m
- Width: 1m
- Length: 1m

Redflow batteries are a containerised unit and can be padlocked to ensure the safety of the site is maintained. No cages or bollards are required to protect the battery or to restrict access.

Battery placement is based on the applicable standard (AS5139). In summary, the standards state that a pre-assembled integrated battery energy storage system shall not be installed:

- a) Within 600mm on any exit, window, door, an appliance, in access walkways or evacuation routes.
- b) Within 900mm below any of the above.
- c) Against a wall where there is a habitable room on the other side unless the wall is of a suitably non-combustible barrier, or there is a non-combustible barrier between the wall and the battery. A surface or barrier material is considered suitably non-combustible if the material is deemed to be not combustible when tested in accordance with AS1530.1. The following are considered non-combustible and do not need to be tested: brick or masonry block, concrete, compressed cement sheeting, ceramic or terracotta tiles.

2.2.3. Structural considerations

No observed structural issues.

3. Delivery

3.1. Delivery Plan

Delivery of a project like this should take around 6 months.

3.2. Indicative Delivery Costs

We estimate the cost of the above to be around \$58,000 ex GST.

The installation above will generate 110 STC's. These STC's will be kept and sold by the installer. The value of the STC's has been subtracted from the total cost of the solar installation and this cost reduction is reflected in the total estimated cost of the facility. If STCs are retired, rather than sold, the above total cost will increase by around **\$4,125 ex GST**.

4. EV Charging Addition

The Alpine Shire Council has requested information to support the possible installation of an EV charging facility at the site.

4.1. Technical Considerations

This site is currently limited by its supply capacity and 10kva transformer supplying the hall. Unfortunately, due to this the site would not be able to host an EV charger without a transformer upgrade. Due to the cost of a transformer upgrade we believe the site is not feasible.

5. Appendix

5.1. Site electrical infrastructure

Detailed photos of site electrical infrastructure can be found at the below link.

https://drive.google.com/drive/folders/14nFDv2yN_w8SsJtzgYwyWaq83SqTdOOn?usp=sharing

5.2. Site structural and layout photos

Detailed photos of structural building integrity and proposed layout locations can be found at the below link.

https://drive.google.com/drive/folders/14qaz0v7pFggnhsx1R5l0_dOWLWtsNWbq?usp=sharing

Contact

Dena Schulz

Project Manager

Email: dena@indigopower.com.au

Ph: 0457 463 554

ABN: 67 629 865 452

Company Name: Indigo Power Ltd

Get in touch

Indigo Power

Old Beechworth Gaol
Corner of William and Ford Streets,
Beechworth VIC 3747, Australia

www.indigopower.com.au

email: connect@indigopower.com.au

ph: 1800 491 739

2022 Greenpeace
Green Electricity Rating



The Green
Electricity
Guide



Business for good